



L202 was changed to 3 turns around L203 using No. 16 26/30 PVC insulated wire

C225 was added. its value is selected for frequency, determine by inspection
 C226 and C227 are selected for frequency, determine by inspection.

Serial Numbers of units affected by this modification:

20,36 through 38,51,55,70,78,83,110,143,205 through 226,235 through 241, through 251,115 and 116,130,138 and 139, 230, and 253 through 267.

Additional Changes:

- C7 was changed to a 470 pf mica from a 220pf mica to adjust gain.
- C69 was changed to a 470 pf mica from a 470 pf disc to improve stability.
- C113 was changed to a 220 pf mica from a 470 pf mica to adjust stability.
- C114 was changed to a 68 pf mica from a 68 pf disc to improve stability.
- C122 is not used most of the time but when it is, it is a 10 pf mica.
- C203 was changed to a .1 disc from a .1 disc to increase decoupling.
- C206 was changed to two .003 mica in parallel from a .005 disc to increase drive.
- C222 was changed to a .0015 mica from a .001 disc to increase drive.
- R302 and R303 were changed to 2.2K ohm from 6.8K ohm to decrease current drive.